

7. (Amended) The arrangement as claimed in claim 6, further comprising an adder which is fed said control signal and said digital signal, an adder output being fed to a modulation input of said modulator.

REMARKS

The present Amendment revises the specification and claims to conform to United States patent practice, before examination of the present PCT application in the United States National Examination Phase. Pursuant to 37 CFR 1.125 (b), applicants have concurrently submitted a substitute specification, excluding the claims, and provided a marked-up copy. All of the changes are editorial and applicant believes no new matter is added thereby. The amendment, addition, and/or cancellation of claims is not intended to be a surrender of any of the subject matter of those claims.

Early examination on the merits is respectfully requested.

Submitted by,

Mark Bergner (Reg. No. 45,877)
Mark Bergner
Schiff Hardin & Waite
Patent Department
6600 Sears Tower
233 South Wacker Drive
Chicago, Illinois 60606-6473
(312) 258-5779
Attorneys for Applicant

CUSTOMER NUMBER 26574

Appendix A
Mark-Ups for Claim Amendments

1. **(Amended)** A method for optimizing an amplitude-modulated optical signal~~[(OSM)], [which is generated]~~**comprising the steps of:**

generating said amplitude-modulated optical signal in a modulator~~[(2)]~~ by modulating an optical signal ~~[(OS)]~~ with ~~[the aid of]~~ a digital signal~~[(DS)]~~;

~~[—characterized]~~

~~[in that the]~~**feeding said** amplitude-modulated optical signal ~~[(OSM) is fed]~~ to a frequency discriminator~~[(5)]~~ which outputs a~~[spectral distribution signal]~~~~[(SV)]~~**spectral distribution signal;**

~~[—in that the]~~~~[spectral distribution signal]~~~~[(SV) is fed]~~**feeding said spectral distribution signal** to a control device ~~[(6)]~~ which is also fed ~~[a]~~**an** adjustable reference signal~~[(RS)]~~; and

~~[in that the]~~**generating a** control signal~~[(SR)]~~ which sets ~~[the]~~**an** operating point of ~~[the]~~**said** modulator~~[(2) is generated]~~ by comparing ~~[the two signals]~~**said adjustable reference signal and said spectral distribution signal.**

~~[2.—]~~~~[The method as claimed in claim 1,]~~

~~[—characterized]~~

2. ~~[in that]~~**(Amended) The method as claimed in claim 1, further comprising the step of separating** a measuring signal ~~[(OMT)]~~ which is fed to ~~[the]~~**said** frequency discriminator~~[(5) is separated]~~ from ~~[the]~~**said** amplitude-modulated optical signal~~[(OSM)]~~.

3. **(Amended)** The method as claimed in claim ~~[1 or 2,]~~**1, further comprising the steps of:**

~~[—characterized]~~

~~[in that the]~~**determining said** spectral distribution signal ~~[(SV) is determined]~~ at ~~[the]~~**a** start of a transmission path~~[,]~~; and ~~[in that the]~~

setting said reference signal ~~[(RS) is set taking account of the]~~**based on** properties of ~~[the]~~**said** transmission path~~[(3)]~~.

4. **(Amended)** The method as claimed in claim ~~[1 or 2,]~~**1, further comprising the steps of:**

~~[—characterized]~~

~~[in that the spectral distribution signal (SV) is determined at the]~~**determining said spectral distribution signal (SV), at a** receiving end~~[,]~~; and

~~[in that the spectral distribution signal (SV)]~~**transmitting said**~~—— in that the spectral distribution signal or a control signal (SR) generated therefrom [is —— transmitted] to [the]said modulator [(2)] provided at [the]a transmitting end.~~

5 ~~[5. —— The method as claimed in one of the preceding claims,]~~
~~[—— characterized]~~

5. [in that the](Amended) 2. The method as claimed in claim 1,
wherein said control signal~~[(SR)]~~ is obtained during periodically occurring time windows~~[(ZF)]~~.

10 6. **(Amended)** An arrangement for optimizing an amplitude-modulated optical signal~~[(OSM)]~~, ~~[having]~~**comprising:**

a light source~~[(1) and];~~

5 a **modulator having an output, said** modulator ~~[(2) to which there are]~~**being** fed an optical signal ~~[(OS)]~~from ~~[the]said~~ light source~~[(1)]~~ and a digital signal ~~[(DS)]~~for amplitude modulation~~[:];~~

~~[—— characterized]~~

20 ~~[in that the]a~~ frequency discriminator~~[(5)]~~ which outputs a spectral distribution signal ~~[(SV)]~~**that** is ~~[corrected]~~**connected** to ~~[the]said~~ output of ~~[the]said~~ modulator~~[(2)]~~ via a splitter~~[(4),]~~and~~[in that]~~

25 a control device~~[(6) is provided]~~ with a reference signal setting device ~~[(7)]~~which is fed ~~[the]said~~ spectral distribution signal~~[(SV)]~~ and which generates a control signal ~~[(SR)]~~which controls ~~[the]an~~ operating point of ~~[the]said~~ modulator~~[(2)]~~.

7. **(Amended)** The arrangement as claimed in claim 6,
~~[—— characterized]~~~~[in that]~~ **further comprising** an adder~~[is provided]~~ which is fed ~~[the]said~~ control signal ~~[(SR)]~~and ~~[the]said~~ digital signal~~[(DS)]~~, ~~[and]~~~~[in that the]an~~ adder output ~~[is]~~**being** fed to a modulation input of ~~[the]said~~ modulator~~[(2)]~~.

[Description] SPECIFICATION

~~[Method and arrangement for optimizing of an amplitude-modulated optical signal]~~

TITLE

METHOD AND ARRANGEMENT FOR OPTIMIZING AN AMPLITUDE-MODULATED OPTICAL SIGNAL

BACKGROUND OF THE INVENTION

FIELD OF THE INVENTION

[0001] The invention relates to ~~[methods according to the preamble of patent claim 1, and to]~~ a method and arrangement for optimizing an ~~[arrangement according to the preamble of claim 6.]~~ amplitude-modulated optical signal.

DESCRIPTION OF THE RELATED ART

[0002] Digital signals are frequently transmitted in optical networks with the aid of amplitude modulation (ASK). A carrier wave is transmitted in the case of one logic state, and no signal/carrier wave is transmitted during the other logic state. ~~[As early as]~~ Early in the modulation (on-off), ~~[what is termed]~~ a "chirp" is produced ~~[in]~~ which changes the wavelength and amplitude of the output signal ~~[and also the amplitude thereof, are changed]~~. The transient component of the chirp causes large variations in the ~~[region of the edges]~~ edge regions, and a sharp increase or decrease ~~[, [sic]]~~ in the wavelength ~~[,]~~; the switch-on edge ~~[being]~~ is of particular importance ~~[,]~~ since the changes occur in the case of a full signal level. The other ~~[,]~~ adiabatic component of the chirp can be kept small by a suitable design of the modulator.

[0003] During transmission of ~~[the]~~ a pulse in a waveguide (glass fiber), self-phase modulation of the carrier occurs ~~[,]~~ (this being a further form of the chirp [,]) in which the wavelength changes likewise, particularly in the

leading edge region and trailing edge region of the pulse.
[Amplitude] Also, amplitude distortions can occur[~~in~~
addition] .

[0004] The two wavelength distortions, including the transient component of the chirp induced by switching on, and the self-phase modulation result in pulse distortion of the baseband signal[~~which~~], contribute (particularly in the case of transmission systems with high bit rates[~~contribute~~]) to limiting the data rate and the transmission range.

[0005] An attempt is usually made to minimize the chirp-induced disturbing influences by setting operating points of Mach-Zehnder modulators or integrated electro-absorption modulators in [the] a test bay. However, resettings must be undertaken when changes occur to the operating parameters.

[0006] British patent document GB 2 308 675 A discloses an arrangement and a method for driving an optical modulator[~~The printed publication~~] and describes the setting of a chirp parameter[~~Monitoring~~] where monitoring the modulated signal is performed at the receiving end[~~in~~] in order to set the chirp parameters via a back channel for pulse compression.

[0007] British patent document GB 2 316 821 A describes an optical time-division multiplex system which compensates the chromatic dispersion of the transmission path by means of controlled chirping of the transmitted signal. Monitoring of the modulated signal is not provided.

[0008] [~~From [sic] the earlier~~] Earlier European patent application EP 0 971 493 A1 likewise describes a method for compensating dispersion and nonlinearities in optical communication systems. In this system, however, it is, for example, the error rate which is measured and the transmission level which is controlled as parameters. Both

measures do not appear to be expedient in modern optical systems.

SUMMARY OF THE INVENTION

[0009] It is therefore the object of the invention to ~~[specify]~~ provide a method and an ~~[arrangements~~ ~~{s ie}]~~ arrangement for permanent optimization of the pulse shape/spectral distribution of an amplitude-modulated optical signal, particularly taking omtp account ~~[-ef]~~ the modulation-induced chirp and the self-phase modulation in optical transmission systems.

[0010] Achievements of this object are specified in the independent claims. Advantageous developments of the invention are specified in the subclaims.

[0011] This object is achieved by a method for optimizing an amplitude-modulated optical signal, comprising the steps of generating the amplitude-modulated optical signal in a modulator by modulating an optical signal with a digital signal; feeding the amplitude-modulated optical signal to a frequency discriminator which outputs a spectral distribution signal; feeding the spectral distribution signal to a control device which is also fed an adjustable reference signal; and generating a control signal which sets an operating point of the modulator by comparing the adjustable reference signal and the spectral distribution signal. The inventive method may further comprise the step of separating a measuring signal which is fed to the frequency discriminator from the amplitude-modulated optical signal. The method may further comprise the steps of determining the spectral distribution signal at a start of a transmission path; and setting the reference signal based on properties of the transmission path. The method may further comprise the steps of determining the spectral distribution signal at a receiving end; and transmitting the spectral

distribution signal or a control signal generated therefrom to the modulator provided at a transmitting end. The control signal may be obtained during periodically occurring time windows.

[0012] This object is also achieved by an arrangement for optimizing an amplitude-modulated optical signal, comprising a light source; a modulator having an output, the modulator being fed an optical signal from the light source and a digital signal for amplitude modulation; a frequency discriminator which outputs a spectral distribution signal that is connected to the output of the modulator via a splitter; and a control device with a reference signal setting device which is fed the spectral distribution signal and which generates a control signal which controls an operating point of the modulator. The arrangement may further comprise an adder which is fed the control signal and the digital signal, an adder output being fed to a modulation input of the modulator.

[0013] The measures according to the invention consist ~~[in]of~~ using quality criteria for optimal modulation of the optical signal to set the operating point of the modulator and ~~[to maintain]~~maintaining the optimum setting by ~~[means]~~way of a control loop.

[0014] An advantageous and simple solution is to derive a measuring signal from the modulated optical digital signal and feed it to a frequency discriminator. The output signal of the ~~[latter is —[sic] led]~~frequency discriminator is transmitted via a control device~~[—[sic]]~~ which determines the operating point of the modulator.

[0015] If the measuring signal is tapped at the receiving end, the properties of the transmission path can be taken into account ~~[by means of]~~via an adjustable reference

signal. The output signal of the modulator is set so as to produce an optimal received signal.

[0016] If a back channel[7] (as a rule, a service channel[7]) is available, a measuring signal can be tapped from the baseband signal and evaluated. The spectral distribution signal output by a phase discriminator, or a control signal generated therefrom, will be transmitted to the source of the signal, i.e., the modulator.

BRIEF DESCRIPTION OF THE DRAWING

[0017] The invention is explained in more detail with the aid of an exemplary embodiment. The Figure is a schematic block diagram showing~~Figure 1 shows~~ a first exemplary embodiment with spectral appraisal.

~~[In the drawing:]~~

~~[Figure 1 shows] [-a first exemplary embodiment with spectral appraisal.]~~

DETAILED DESCRIPTION OF THE INVENTION

[0018] The Figure[-1] shows a first exemplary embodiment of a control loop for optimizing the modulation-induced chirp. The block diagram shows only the modules essential to the invention. A laser provided as a narrow-band light source 1 supplies an optical signal OS of high frequency, which is fed to a modulator 2. The ~~[latter]~~ optical signal is ~~[submitted]~~ subjected to amplitude modulation by ~~[means]~~ way of a digital signal DS (on-off keying). The modulated optical signal OSM, output by the modulator, is fed into an optical conductor of a transmission path 3 and transmitted. A measuring signal OMT of low power is tapped from the modulated signal via a splitter (coupler) 4 and fed to a frequency discriminator 5. The ~~[latter]~~ frequency discriminator can include, for example, an optical filter whose edge, which is as rectilinear as possible, is used for frequency demodulation. ~~[The demodulated optical signal is~~

~~converted into an electric spectral distribution signal SV and fed to a control device 6. The] [latter is fed as reference input] [an adjustable reference signal RS] [which] [is generated via a reference setting device] [7,] [a voltage divider in the example] [The control device supplies] [as] [manipulated variable a control signal SR which sets the operating point of the modulator and thereby optimizes the transient chirp of the modulated optical signal even in the case of changes in the component properties.]~~

[0019] The demodulated optical signal is converted into an electric spectral distribution signal SV and fed to a control device 6. The latter is fed as reference input spectral distribution signal SV is fed as a reference input; an adjustable reference signal RS which is generated via a reference setting device 7, 7 (a voltage divider in the example). The control device supplies as a manipulated variable a control signal SR which sets the operating point of the modulator and thereby optimizes the transient chirp of the modulated optical signal even in the case of changes in the component properties.

[0020] An optimum setting is given when the receive signal is optimal. A measurement at the receiving end is actually required for this purpose. However, a compact replacement transmission path used for the setting likewise permits an exact setting. The spectral distribution signal serves as a criterion during setting. A specific envelope of the modulated signal corresponds to this criterion, and can likewise serve as a criterion.

[0021] If the properties of the transmission path are known, they are already taken into account during setting, and the spectral distribution (or a pulse shape) is set so as to produce optimal receiving conditions.

[0022] Since the spectral distribution signal SV can be weakly dependent on the ~~[on the {sic}]~~ bit sequence of the digital signal, it can be expedient to have a time window ZF during which specific bit sequences are transmitted and the control signal is determined.

[0023] ~~[It remains to add that the]~~ The control signal RS and the digital signal can be combined by an adder, and the aggregate signal is then fed to the modulation input of the modulator.

[0024] As in the arrangement illustrated in ~~[figure]~~ Figure 1, it is also possible, of course, to appraise the spectral distribution of a modulated optical signal at the receiving end, and a corresponding spectral distribution signal or else the control signal derived therefrom ~~[is transmitted {sic}]~~ may be provided to the transmitting part.

[0025] The above-described method and apparatus are illustrative of the principles of the present invention.
Numerous modifications and adaptations will be readily apparent to those skilled in this art without departing from the spirit and scope of the present invention.

	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

~~[Figure 1]~~

LIST OF REFERENCE SYMBOLS

DS Digital signal
DD Demodulated digital signal
1 Laser
2 Modulator
3 Optical conductor
4 Splitter
5 Discriminator
6 Control device
7 Reference setting device
RS Reference signal
OS Optical signal
OSM Amplitude-modulated optical signal
OMT Measuring signal
SV Spectral distribution signal
SF Control signal
ZF Time window
8 Summing device
9 Receiving device
10 Optoelectric transducer
11 Amplifier
12 Decision circuit
13 Data output
14 Measuring instrument appraising device
15 Evaluation device
16 Controller
17 Modulation input
18 Transmitting device
19 Receiving device
SE Setting signal

FIG 1

